

PRODUCT-DETAILS

# XLP00

## XLP00 Fuse Switch Disconnecter



### Información General

Extended Product Type	XLP00
Product ID	1SEP101890R0001
EAN	7025840013396
Catalog Description	XLP00 Fuse Switch Disconnecter
Long Description	XLP00,3-pole,160A, without clamps or bolts

### Descargas Populares

Data Sheet, Technical Information	1SEC312012D0201
-----------------------------------	-----------------

### Dimensiones

Product Net Width	105 mm
Product Net Height	187 mm
Product Net Depth / Length	90 mm
Product Net Weight	0.55 kg

### Technical

Rated Operational Current AC-21B (I <sub>e</sub> )	(690 V) 125 A
--	---------------

Rated Operational Current AC-22B (I <sub>e</sub> )	(500 V) 160 A (800 V) 63 A
Rated Operational Current AC-23B (I <sub>e</sub> )	(400V) 125 A
Rated Impulse Withstand Voltage (U <sub>imp</sub> )	Main Circuit 8 kV
Rated Operational Voltage	400 V AC 500 V AC 690 V AC
Rated Frequency (f)	Main Circuit 50/60 Hz
Rated Conditional Short-Circuit Current (I <sub>nc</sub> )	(690 V) 50 kiloampere rms
Handle Type	Front cover 3P
Fuse Size	NH00 NH000
Fuse System	DIN
Standards	IEC60947-3
Special Functions	Not Included
Mounting Type	Baseplate
Number of Poles	3
Degree of Protection	IP30
Terminal Type	Lug terminals

### Certificados y Declaraciones (Número de Documento)

Declaration of Conformity - CE	1SEP500050P0001
--------------------------------	-----------------

### Información de Embalaje

Package Level 1 Units	shrink-wrap 1 piece
Package Level 1 Width	105 mm
Package Level 1 Depth / Length	90 mm
Package Level 1 Height	187 mm
Package Level 1 Gross Weight	0.55 kg
Package Level 1 EAN	7025840013396
Package Level 2 EAN	7025840013396

### Clasificaciones

Object Classification Code	S
ETIM 4	EC001040 - Fuse switch disconnecter
ETIM 5	EC001040 - Fuse switch disconnecter
ETIM 6	EC001040 - Fuse switch disconnecter
ETIM 7	EC001040 - Fuse switch disconnecter
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

---

## Categorías

---

Productos y sistemas de baja tensión → Interruptores seccionadores-fusible → Interruptores desconectores fusible → EasyLine

